MP series







SMP35/SMP50


Channel Input Type of Multifunctional Product



- Switch for sound pattern selection
- 2 SDcard slot for MP3
- Switch for play mode selection
- Switch for channel selection
- Switch for volume adjustment

Switch for Sound

· Switch No1. allows choosing one option between pre-recorded sound and SDcard



Bit input mode selection from 6 groups

- 001: WS(5 Warning sounds)
- 010: WP(5 Special warning sounds 1st group)
- 011: WM(5 Melodies)
- 100: WA(5 Alarms)
- 101: WO(5 Special warning sounds 2nd group)
- 110: WN(5 Special warning sounds 3rd group)

Selection between pre-recorded sound mode and SDcard sound mode

0: pre-recorded sound mode

- 1: SDcard sound mode
- 30 pre-recorded sounds offered (5 warning sounds, 5 special warning sounds 1st group, 5 melodies, 5 alarms, 5 special warning sounds 2nd group, 5 special warning sounds 3rd group)
- External MP3 sound support (SDcard)
- Binary input : 30 Channels
- Bit input : 5 Channels (6 sound groups)
- · A multi-functional product that can use an SDcard for MP3 playback
- Details on how to setup the multi-functional speakerphone are on page 28

Self Stand Multi-Functional Electric Horns



Common Specifications(SMP35/SMP50)

- · Can prevent cross talk of different voice environments by selecting an audio signal fit for the specific environment and condition
- 30 pre-recorded sound type and supports Binary input mode and Bit input mode
- Binary input mode can playback 30 sound tones by using sound tone select switch
- · Volume adjustment and sound selection switches located inside the unit. SDcard in the unit offers convenient operation
- · SDcard type allows the user to input the proper voice messages for specific operating conditions
- Support MP3 file and user can input user defined sound
- Tightly sealed structure that blocks dust with IP65 protection rating- suitable for outdoor
- · Materials: Housing-ABS, Resonance chamber-ABS, Bracket-STS
- Ambient operating temperature : -25°C to +50°C
- Protection rating: IP65
- · Certificates : CE Compliant
- · Compliant with RoHS directive

SMP35 Multifunctional Self Stand Type Electric Signal Horn(Supports Warning Sound/ MP3)

· Volume: Max 115dB at 1m

Model number	Voltage	Current	Built-in Sound and dB	Input Method/ No. of Ch	Certificate	Weight
SMP35	DC12V-24V	Max 0.800A	• Warning : 115dB • MP3 : 113dB	·	C€	0.76kg
	AC110V-220V	Max 0.290A			AC only	1.03kg

- * DC type model has a free-voltage range of 10V-30V.
- * AC type model has a free-voltage range of 100V-240V.


SMP50 Multifunctional Self Stand Type Electric Signal Horn(Supports Warning Sound/ MP3)


- · Powerful 50W unit can generate high signal sound
- · Volume: Max 123dB at 1m


Model number	Voltage	Current	Built-in Sound and dB	Input Method/ No. of Ch	Certificate	Weight
	DC12V	1.800A	• Warning : 123dB • MP3 : 118dB	Bit Input : 5Ch Binary Input : 30Ch	C € AC only	0.95kg
SMP50	DC24V	1.000A				
	AC110V-220V	Max 0.600A				1.23kg

* AC type model has a free-voltage range of 100V-240V.

Technical Diagram





















Obstruction Lights



Liahts





(Units:mm)





Industrial I FD Lights

Qlight

SMP series

Self Stand Multi-Functional Electric Horns

	Category	Ch	Sound	
		Ch1	Fire.A-ANG	
	□ \A/a maina m	Ch2	Emergency WA-U(Yelp)	
WS	5 Warning Sounds	Ch3	Ambulance PI-PO(Hi-low)	
	Sourius	Ch4	Machinery Fault	
		Ch5	High Expansion	
	5.0	Ch1	Fire.A-ANG	
WP	5 Special Warning	Ch2	Abandon Alarm	
	Sounds (1 st group)	Ch3	Machinery Fault	
		Ch4	High Expansion	
	(. g.oup)	Ch5	7 Short Pl. / 1 Long	
		Ch1	Sweet Home	
	5 Melodies	Ch2	For Elise	
WM		Ch3	Cuckoo's Waltz	
		Ch4	Piano Sonata	
		Ch5	Turkish March	
		Ch1	Beep Intermittent	
	5 Alarms	Ch2	Door Chime	
WA		Ch3	Phone Ring	
		Ch4	PI.PI.PI Short	
		Ch5	Tripping Beat	
	5.0	Ch1	Phone Ring	
	5 Special Warning	Ch2	Police	
WO	Sounds	Ch3	Emergency	
	(2 nd group)	Ch4	Phone Ring 2	
	(<u> </u>	Ch5	911 siren	
	F Ci-I	Ch1	Do-ong Do-ong	
WN	5 Special Warning	Ch2	Di- Di-	
	Sounds	Ch3	PI.PI.PI long	
	(3 rd group)	Ch4	Li long Li long	
	(5 group)	Ch5	Siren	


Sound Selection and Wiring Instructions


• Standard : Select using the switch inside of the unit

EXTERNAL CONTACT

 Customized wiring in case of external contact or transistor wiring type as sound tone selector (Model name : -LC)

SMP35/ SMP50-DC/AC





- DC type : Black output is negative(-)
- Channel selection, 5 sounds played for Bit input and 30 sound played for binary input
- ** Please refer to page 28 for detailed channel input instructions. (Wiring instruction is substituted for channel selection switch.)

Ordering Spe	cifications	
SMP50	- 110/220	- LC
[Model number] • SMP35	[Voltage] • 12/24-DC12V-24V • 110/220-AC110V-220V	[Sound selection] • Standard - Built-in Switch
• SMP50	• 12-DC12V • 24-DC24V • 110/220-AC110V-220V	• LC - External contact

SN-1

Small Size Electric Horn












Ordering Specification

Ordering Specification					
SN-1	_	12			
[Model number]		[Voltage]			
• SN-1		• 12-DC12V • 24-DC24V			

SN-1 Max 100dB

• 1 warning sound and cost effective model for DC only



(Units:mm)

